DS Instruments - Phase Shifter SCPI Command List

Command	Example 1	Example 2	Description
PHASE	PHASE 90	PHASE -30	Set phase shift in degrees
PHASE?			Return current phase setting
*IDN?			Return the SCPI identification string
*PING?			returns "PONG!" if device is responding
SYST:ERR?			Returns any pending error codes
*RST			Reset unit now
*DISPLAY	*DISPLAY OFF	*DISPLAY ON	Power on of off the display
*BUZZER	*BUZZER ON	*BUZZER OFF	Mute the buzzer
*SAVESTATE			Save frequency & attenuation as boot defaults
*UNITNAME	*UNITNAME Bob	*UNITNAME DEV-34	Set a unique name in flash memory
*UNITNAME?			Return this device's name

Command terminator is LINEFEED ("\n")

Version 1.5 - (COM BAUD: 115200)